arXiv:1109.1138v1 [nlin.CD] 6 Sep 2011

An analytical limitation for time-delayed feedback control in autonomous systems

Edward W. Hooton[1] and Andreas Amann[1, 2, *]
[1] *School of Mathematical Sciences, University College Cork, Ireland*
[2] *Tyndall National Institute, University College Cork, Lee Maltings, Cork, Ireland*

We prove an analytical limitation on the use of time-delayed feedback control for the stabilization of periodic orbits in autonomous systems. This limitation depends on the number of real Floquet multipliers larger than unity, and is therefore similar to the well-known odd number limitation of time-delayed feedback control. Recently, a two-dimensional example has been found, which explicitly demonstrates that the unmodified odd number limitation does not apply in the case of autonomous systems. We show that our limitation correctly predicts the stability boundaries in this case.

PACS numbers: 02.30.Ks, 05.45.Gg

When chaotic systems started to get wider scientific attention during the 1960s, chaos was considered to be a mathematically interesting concept with little practical applications. This has changed dramatically in the 1990s when Ott, Grebogi and Yorke [1] introduced a method to stabilize Unstable Periodic Orbits (UPOs) within the chaotic attractor using small perturbations. Since then, the subject of chaos control has been vigorously developed [2, 3].

One simple method to select a particular UPO within a chaotic attractor is via the time-delayed feedback control due to Pyragas [4]. Because no detailed knowledge of the chaotic system or its attractor is required, this method proved to be easy to implement and widely applicable [5–12]. However, it was claimed by Nakajima [13] that the time-delayed feedback control is not able to stabilize a UPO with an odd number of real Floquet multipliers larger than unity. While this odd number limitation was proved in [13] for the case of hyperbolic UPOs in non-autonomous systems, it was also stated that the same restriction should apply for the autonomous case "with a slight revision" (footnote 2 of [13]). Over the following years the odd number limitation was used by many researchers, and it seemed to be supported by experimental and numerical evidence even for autonomous systems, although in this case a strict proof was missing. Recently, Fiedler et al. [14] discovered a UPO in an autonomous two-dimensional system, which has precisely one Floquet multiplier larger than one, and can be stabilized by the time-delay feedback control scheme. This directly refuted the common belief that the odd number limitation is also valid for systems without explicit time-dependence. Autonomous systems are by far the most dominating type of systems considered in nonlinear science, and time-delayed feedback control is one of the most practical methods for stabilizing (or destabilizing) periodic orbits. Therefore any limitation on the use of time-delayed feedback control is not only important from an academic point of view, but also has practical implications for the many applications of time-delayed feedback in real-world systems.

In this Letter we give an analytical condition under which the time-delayed feedback control is not successful in autonomous systems. Similarly to the odd number limitation, this condition involves the number of real Floquet multipliers larger than unity, but it is now modified by a term which takes the action of the control force in the direction of the periodic orbit into account. Our proof follows to a large extent the proof of the original odd number limitation given in [13] but now implements the necessary modification for the autonomous case. As a first application we show that our limitation correctly reproduces the boundaries of stability for the two dimensional system studied in [14–16], which originally served as a counter example of the unmodified odd number limitation.

Let us start with an uncontrolled dynamical system $\dot{x}(t) = f(x(t))$ with $x(t) \in \mathbb{R}^n$ and $f : \mathbb{R}^n \to \mathbb{R}^n$ and implement the time-delayed feedback control in the form

$$\dot{x}(t) = f(x(t)) + K[x(t-\tau) - x(t)], \tag{1}$$

where K is an $n \times n$ control matrix, and τ is a positive parameter. If the uncontrolled system has a τ-periodic solution $x^*(t) = x^*(t+\tau)$, then the form of (1) implies that $x^*(t)$ is also a solution of (1) for any choice of the control matrix K.

In order to assess the stability of the periodic orbit $x^*(t)$ in the controlled case, it is convenient to first introduce the the fundamental matrix $\Phi(t)$ for the *uncontrolled* system as the solution of the initial value problem

$$\dot{\Phi}(t) = Df(x^*(t))\,\Phi(t); \qquad \Phi(0) = \mathbb{I}, \tag{2}$$

where $Df(x^*(t))$ denotes the Jacobian of f evaluated at $x^*(t)$, and $\mathbb{I}$ is the $n \times n$ identity matrix. The generalized eigenvalues $\{\mu_1, \ldots, \mu_n\}$ of $\Phi(\tau)$ are the Floquet multipliers associated with the periodic orbit $x^*(t)$. We also define the matrix $W(t) = (v_1(t), \ldots, v_n(t))$ such that its kth column $v_k(t) \in \mathbb{C}^n$ is given by $v_k(t) = \Phi(t)\, v_k(0)$ and the set $\{v_1(0), \ldots, v_n(0)\}$ is a complete set of generalized eigenvectors of $\Phi(\tau)$. For each t, the set $\{v_1(t), \ldots, v_n(t)\}$ provides a local (but in general not τ-periodic) basis at the position $x^*(t)$ along the orbit. Since we consider an autonomous system we also observe that $\dot{x}^*(0) = \Phi(\tau)\,\dot{x}^*(0)$, i.e. one of the Floquet multipliers is equal to unity. It is therefore convenient to choose $v_1(t) = \dot{x}^*(t)$ and $\mu_1 = 1$. By defining

$$\hat{K}(t) = [W(t)]^{-1} K W(t) \tag{3}$$

we transform the control matrix to this local basis. As we will see in the following the $(1,1)$ component of the matrix $\hat{K}(t)$, which we denote by $\hat{K}_{11}(t)$, plays a decisive role in assessing the stability of the controlled orbit $x^*(t)$. Some intuition for the quantity $\hat{K}_{11}(t)$ can be obtained if we expand the result of applying the control matrix to $\dot{x}^*(t)$ in the local basis via

$$K\dot{x}^*(t) = \hat{K}_{11}(t)\,\dot{x}^*(t) + \sum_{k=2}^{n} \hat{K}_{1k}(t)\, v_k(t)\,. \tag{4}$$

In loose terms we can therefore interpret the quantity $\hat{K}_{11}(t)$ as the action of the control matrix K projected in the tangential direction of the orbit at time t. Note that $\hat{K}_{11}(t)$ is well defined and in particular not affected by any reordering or rescaling of the $v_k(t)$ for $k \geq 2$. Using this definition of $\hat{K}_{11}(t)$ we are now in a position to formulate the main result.

Theorem: Let $x^*(t)$ be a τ-periodic orbit of (1) which for $K = 0$ possesses m real Floquet multipliers larger than unity and precisely one Floquet multiplier equal to unity. Then $x^*(t)$ is an unstable solution of the time-delayed system (1) if the condition

$$(-1)^m \left(1 + \int_0^\tau \hat{K}_{11}(t)\,dt\right) < 0, \tag{5}$$

is fulfilled. Here $\hat{K}_{11}(t)$ is defined as in (4).

Before we proceed with the proof of the theorem, let us briefly discuss its significance. The theorem provides an analytical limitation on the use of time-delayed feedback control, and states that time-delayed feedback can *only* successfully stabilize a periodic orbit, if the condition (5) is violated. We stress however that the converse is not implied by the theorem, i.e. a violation of (5) alone does *not* guarantee that time-delayed feedback will successfully stabilize a given periodic orbit. The theorem is only applicable to periodic orbits with exactly one Floquet multiplier equal to one. In practice this is not a serious restriction, since it is fulfilled for any orbit which is *hyperbolic* in the context of an autonomous system.

The number m of real Floquet multipliers larger than unity only enters in the form $(-1)^m$ in condition (5), and we can therefore divide the discussion into the two cases of odd and even m. In the case of odd m the original odd number limitation suggests that it is not possible at all to use the time-delayed feedback scheme to stabilize the periodic orbit. Our theorem now modifies this statement and allows for successful stabilization if the necessary condition

$$\int_0^\tau \hat{K}_{11}(t)\,dt < -1, \tag{6}$$

is fulfilled. Condition (6) can therefore guide the selection of an appropriate control matrix K, which enables the stabilization of periodic orbits with odd m. In particular it is required that the average of $\hat{K}_{11}(t)$ along the periodic orbit is negative. We also note that odd m implies that the orbit is unstable in the uncontrolled case, and obviously (6) is not fulfilled for $K = 0$. Without knowledge of the limitation (6) it is difficult to construct a suitable control matrix K and this might explain why numerical and experimental evidence seemed to wrongly indicate that the original odd number limitation [13] is also valid in the autonomous case.

In contrast to previous results, the condition (5) also provides a limitation in the case of an even number m of real Floquet multipliers larger than unity. In this case an orbit can only be stabilized if the limiting condition

$$\int_0^\tau \hat{K}_{11}(t)\,dt > -1 \tag{7}$$

is fulfilled. Note that this condition is automatically fulfilled for $K = 0$ and therefore only provides a limitation on time-delayed feedback control in the large coupling regime. Condition (7) is however also useful, if it is desired to destabilize a stable periodic orbit using time-delayed feedback. This can be achieved by a control matrix K which violates (7).

Let us now proceed with the proof of the theorem, which uses many ideas from [13] but now takes particular consideration of the autonomous case. The essential tools in the proof are the two functions $F(\nu)$ and $G(\nu)$ defined by [13]

$$G(\nu) = \det[\nu\mathbb{I} - \Phi(\tau)] \tag{8}$$

$$F(\nu) = \det[\nu\mathbb{I} - \Psi_\nu(\tau)] \tag{9}$$

where $\Psi_\nu(t)$ solves the initial value value problem

$$\dot{\Psi}_\nu(t) = \left[Df(x^*(t)) + \left(\nu^{-1} - 1\right)K\right]\Psi_\nu(t)\,, \quad \Psi_\nu(0) = \mathbb{I}. \tag{10}$$

By direct differentiation it can be verified that the solution of (10) can also be expressed as [13]

$$\Psi_\nu(t) = \Phi(t)\left[\mathbb{I} + \left(\nu^{-1} - 1\right)\int_0^t \Phi^{-1}(u)\,K\Psi_\nu(u)\,du\right]. \tag{11}$$

In order to prove the theorem let us first show the following lemma:

Lemma: If for a given τ-periodic orbit $x^*(t)$ with precisely one Floquet multiplier equal to unity the condition $F'(1) < 0$ holds, then $x^*(t)$ is an unstable solution of the time-delayed system (1).

Proof of the Lemma: From (10) it follows that $\Psi_\nu(t)$ is bounded in the limit of $\nu \to +\infty$, and therefore (9) implies that $F(\nu) \approx \nu^n \to +\infty$ in the limit of $\nu \to +\infty$. In an autonomous system we know that $\mu_1 = 1$ is an eigenvalue of $\Phi(\tau)$ and it therefore follows from (8) that $G(1) = 0$. But since from (10) it follows that $\Psi_1(t) = \Phi(t)$ we also have $F(1) = G(1) = 0$. Thus $F(\nu)$ is a continuous function, which vanishes at $\nu = 1$, has a negative slope at $\nu = 1$, and diverges to $+\infty$ for large ν. By the intermediate value theorem there exists at least one $\nu_c > 1$ with $F(\nu_c) = 0$. From (9) it then follows that there exists a vector $w_c(0) \in \mathbb{R}^n$ with $\Psi_{\nu_c}(\tau) w_c(0) = \nu_v w_c(0)$ and we can define $w_c(t) = \Psi_{\nu_c}(t) w_c(0)$. Using this definition of $w_c(t)$ and the fact that $w_c(-\tau) = \nu_c^{-1} w_c(0)$ it is straightforward to check that the function $x(t) = x^*(t) + \epsilon w_c(t)$ solves the original time-delayed system (1) up to first order in ϵ. However, since $\nu_c > 1$ and $w_c(k\tau) = \nu_c^k w_c(0)$, the term $\epsilon w_c(t)$ grows exponentially in time, and therefore $x^*(t)$ is an unstable solution of the time-delayed system (1). This completes the proof of the lemma.

Proof of the Theorem: To complete the proof of the theorem, it now remains to show that the condition (5) implies that $F'(1) < 0$. Under this condition the above lemma then implies that the orbit $x^*(t)$ is unstable and thereby proves the theorem. Since $F(1) = 0$ we can write $F'(1) = \lim_{\epsilon \to 0} F(1+\epsilon)/\epsilon$. To assess the sign of $F'(1)$ it is therefore necessary to evaluate $F(1+\epsilon)$ up to first order in ϵ. According to (9) we can achieve this by first evaluating $\Psi_\nu(t)$ at $\nu = 1 + \epsilon$. Using the representation (11) we write

$$\begin{aligned}\Psi_{1+\epsilon}(t) &= \Phi(t)\left[\mathbb{I} - \frac{\epsilon}{1+\epsilon}\int_0^t \Phi^{-1}(u) K \Psi_{1+\epsilon}(u)\, du\right] \\ &= \Phi(t)\left[\mathbb{I} - \epsilon \int_0^t \Phi^{-1}(u) K \Phi(u)\, du\right] + O\left(\epsilon^2\right).\end{aligned}$$

Then in first order of ϵ we obtain from (9)

$$F(1+\epsilon) = \det\left[M^0 + \epsilon M^1\right] \tag{12}$$

where we have defined the two matrices

$$\begin{aligned}M^0 &= \mathbb{I} - \Phi(\tau), \\ M^1 &= \mathbb{I} + \Phi(\tau)\int_0^t \Phi^{-1}(u) K \Phi(u)\, du.\end{aligned}$$

We can now use the previously defined matrix $W(0)$, whose columns $v_k(0)$ form a complete set of the generalized eigenvectors of $\Phi(\tau)$. We did not yet fix the scaling and order of the $v_k(0)$ for $k > 1$ previously, and we can now choose generalized eigenvectors in such a way that the matrix $\hat{\Phi}(\tau) = W(0)^{-1} \Phi(\tau) W(0)$ is in the Jordan normal form. Transforming the argument of the determinant in (12) to this basis we obtain

$$F(1+\epsilon) = \det\left[W(0)^{-1}\left(M^0 + \epsilon M^1\right) W(0)\right] \tag{13}$$

$$= \det\left[\mathbb{I} - \hat{\Phi}(\tau) + \epsilon\left(\mathbb{I} + \hat{\Phi}(\tau)\int_0^\tau \hat{K}(u)\, du\right)\right] \tag{14}$$

where we have used $W(0)^{-1} \Phi^{-1}(u) K \Phi(u) W(0) = W(u)^{-1} K W(u) = \hat{K}(u)$. Using the Jordan normal form of $\hat{\Phi}(\tau)$ and the fact that $\mu_1 = 1$ we find

$$\mathbb{I} - \hat{\Phi}(\tau) = \begin{pmatrix} 0 & 0 & 0 & \cdots & 0 \\ 0 & 1-\mu_2 & * & \ddots & \vdots \\ \vdots & \ddots & \ddots & \ddots & 0 \\ \vdots & & \ddots & \ddots & * \\ 0 & \cdots & \cdots & 0 & 1-\mu_n \end{pmatrix} \tag{15}$$

where the entries indicated by $*$ can be either 0 or -1. Since all entries in the first column and first row of the matrix $\mathbb{I} - \hat{\Phi}(\tau)$ vanish, the only contribution to the determinant (14) up to first order in ϵ is given by

$$\begin{aligned}F(1+\epsilon) &= \epsilon\left(\mathbb{I} + \hat{\Phi}(\tau)\int_0^\tau \hat{K}(u)\, du\right)_{(1,1)} \prod_{k=2}^n (1-\mu_k) \\ &= \epsilon\left(1 + \int_0^\tau \hat{K}_{11}(u)\, du\right) \prod_{k=2}^n (1-\mu_k).\end{aligned}$$

The product $\prod_{k=2}^n (1-\mu_k)$ does not vanish, since it was assumed that $\mu_1 = 1$ is the only Floquet multiplier equal to unity. Each real Floquet multiplier larger than unity contributes a negative factor to this product, while pairs of complex conjugated Floquet multipliers or real Floquet multipliers smaller than unity do not change its sign. We can therefore write $\operatorname{sgn}\left(\prod_{k=2}^n (1-\mu_k)\right) = (-1)^m$ and conclude that

$$F'(1) < 0 \Leftrightarrow (-1)^m \left(1 + \int_0^\tau \hat{K}_{11}(u)\, du\right) < 0.$$

This means that condition (5) implies a negative $F'(1)$ and it then follows from the lemma that $x^*(t)$ is unstable. This concludes the proof of the theorem.

Let us now compare our theorem and its proof with the proof of the original odd number limitation (theorem 2 in [13]), which states that a *hyperbolic* UPO of a non-autonomous system with an odd number m of real Floquet multipliers larger than unity can not be stabilized using time-delayed feedback control. We stress that the term *hyperbolic orbit* in the context of a non-autonomous system means that the orbit has *no* Floquet multipliers equal to unity. In contrast, for an autonomous system the term *hyperbolic orbit* denotes an orbit with *precisely one* Floquet multiplier equal to unity [17]. In other words, while any autonomous system can be trivially associated with a non-autonomous system of arbitrary period, any hyperbolic orbit in the autonomous system becomes a non-hyperbolic orbit in the associated non-autonomous system. The proof in [13] uses the functions $G(\nu)$ (8) and $F(\nu)$ (9). Under the condition that all Floquet multipliers differ from one, it can be seen from the expression $F(1) = G(1) = \prod_{k=1}^n (1-\mu_k)$ that $F(1) < 0$ for odd m. From the fact that $\lim_{\nu \to \infty} F(\nu) = +\infty$ it then follows that there exists a $\nu_c > 1$ with $F(\nu_c) = 0$. Similar to our proof it is then shown in [13] that this implies that



Figure 1. The functions $G(\nu)$ (solid lines) and $F(\nu)$ (dashed lines) and the slope $F'(1)$ (dotted lines) for the system defined in (16). The parameters are $R^2 = 0.02$, $\gamma = -10$, $\tau = \frac{2\pi}{1+R^2\gamma}$ and $\beta = \frac{\pi}{4}$. For the control strength parameter we use $b_0 = 0.01$ (left hand panel) and $b_0 = 0.04$ (right hand panel).

the periodic orbit is an unstable solution of the time-delayed feedback system. We therefore conclude that the odd number limitation as stated in theorem 2 of [13] is formally correct if the term *hyperbolic* is understood in the context of non-autonomous systems. However, this hyperbolicity condition is explicitly violated in the autonomous limit and the odd number limitation makes no statement for systems without explicit time dependence, which is by far the most significant case in practice.

The first autonomous example, where a UPO with odd m was stabilized using time-delayed feedback control was given in [14] and provided a counter example which showed that the original odd number limitation can not be applied to the autonomous case without modification. It is therefore important to check that our limitation (6) correctly handles this case. Let us consider the dynamical system for $z(t) \in \mathbb{R}^2$ given by [14, 15]

$$\dot{z}(t) = \left[J\frac{2\pi}{\tau} + (1+J\gamma)\left(|z(t)|^2 - R^2\right)\right] z(t) + b_0 \begin{pmatrix} \cos\beta & -\sin\beta \\ \sin\beta & \cos\beta \end{pmatrix} [z(t-\tau) - z(t)] \tag{16}$$

with the four real parameters $\tau > 0$, $R > 0$, $b_0 \geq 0$, β, and using $\gamma = \frac{1}{R^2}\left(\frac{2\pi}{\tau} - 1\right)$ and $J = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix}$. For $b_0 = 0$ we find the τ-periodic orbit $z^*(t) = R\left(\cos(2\pi t/\tau), \sin(2\pi t/\tau)\right)^T$. A short calculation shows that the two Floquet multipliers are given by $\mu_1 = 1$ and $\mu_2 = \exp\left(2R^2\tau\right) > 1$ which implies $m = 1$. The local basis functions can be expressed as $v_1(t) = \dot{z}^*(t)$ and $v_2(t) = \exp\left(2R^2 t\right)\left(z^*(t) + \gamma\frac{\tau}{2\pi}\dot{z}^*(t)\right)$ and we can then use (4) to calculate $\hat{K}_{11}(t) = b_0(\cos\beta + \gamma\sin\beta)$. For a successful stabilization condition (6) therefore requires that

$$b_0(\cos\beta + \gamma\sin\beta)\tau < -1. \tag{17}$$

This agrees with the previous stability condition given in [15]. In this example it is possible to explicitly calculate the functions $F(\nu)$ and $G(\nu)$ which are defined by (8) and (9), respectively. In the left hand panel of Fig. 1 the corresponding plots are shown for a relatively low value of the control strength b_0, where the condition (17) is not fulfilled. In this case we observe that $F(1) = 0$ and the slope $F'(1)$ is negative. Therefore the function $F(\nu)$ needs to cross the zero axis at a point larger than unity and the periodic orbit is unstable. In the right hand panel of Fig. (1) the control strength b_0 is big enough to satisfy condition (17). Then the slope $F'(1)$ is positive and the function $F(\nu)$ does not cross the zero axis at values larger then unity. This is a necessary condition for the stability of the periodic orbit under time-delayed feedback control.

In conclusion, we have proved an analytical limitation on the use of time-delayed feedback control in autonomous systems. This limitation depends on the number of real Floquet multipliers larger than unity, and on the quantity $\hat{K}_{11}(t)$ defined in equation (4), which quantifies the action of the control matrix in the direction of the orbit. While the limitation is valid for arbitrary dimensions, we have demonstrated its usefulness in a well studied two-dimensional system, for which the original odd number limitation does not apply. The knowledge of this limitation will provide an important guidance for the design of time-delayed feedback implementations in practical applications.

This work was supported by Science Foundation Ireland under Grant Number 09/SIRG/I1615.

---

[*] a.amann@ucc.ie

[1] E. Ott, C. Grebogi, and J. A. Yorke, Phys. Rev. Lett. **64**, 1196 (1990).

[2] E. Schöll and H. G. Schuster, eds., *Handbook of Chaos Control*, 2nd ed. (Wiley-VCH, Weinheim, 2007).

[3] S. Boccaletti, C. Grebogi, Y. C. Lai, H. Mancini, and D. Maza, Phys. Rep. **329**, 103 (2000).

[4] K. Pyragas, Phys. Lett. A **170**, 421 (1992).

[5] K. Pyragas and A. Tamaševičius, Phys. Lett. A **180**, 99 (1993).

[6] W. Just, T. Bernard, M. Ostheimer, E. Reibold, and H. Benner, Phys. Rev. Lett. **78**, 203 (1997).

[7] D. W. Sukow, M. E. Bleich, D. J. Gauthier, and J. E. S. Socolar, Chaos **7**, 560 (1997).

[8] M. G. Rosenblum and A. S. Pikovsky, Phys. Rev. Lett. **92**, 114102 (2004).

[9] S. Schikora, P. Hövel, H. J. Wünsche, E. Schöll, and F. Henneberger, Phys. Rev. Lett. **97**, 213902 (2006).

[10] J. Sieber, A. Gonzalez-Buelga, S. A. Neild, D. J. Wagg, and B. Krauskopf, Phys. Rev. Lett. **100**, 244101 (2008).

[11] M. Tlidi, A. G. Vladimirov, D. Pieroux, and D. Turaev, Phys. Rev. Lett. **103**, 103904 (2009).

[12] A. Englert, W. Kinzel, Y. Aviad, M. Butkovski, I. Reidler, M. Zigzag, I. Kanter, and M. Rosenbluh,

Phys. Rev. Lett. **104**, 114102 (2010).

[13] H. Nakajima, Phys. Lett. A **232**, 207 (1997).

[14] B. Fiedler, V. Flunkert, M. Georgi, P. Hövel, and E. Schöll, Phys. Rev. Lett. **98**, 114101 (2007).

[15] W. Just, B. Fiedler, M. Georgi, V. Flunkert, P. Hövel, and E. Schöll, Phys. Rev. E **76**, 026210 (2007).

[16] V. Flunkert and E. Schöll, Phys. Rev. E **84**, 016214 (2011).

[17] Y. A. Kuznetsov, *Elements of Applied Bifurcation Theory*, 3rd ed. (Springer, New York, 2004).